

Test- and transitional connecting part, size 0, 24 kV, 250 A

To fulfill multiple usage requirements, the component is designed with 45° angle.

They are used as transitional connecting parts when transformers that are equipped with CONNEX-bushings are connected to blank (overhead) lines.

They are used as CONNEX test connecting parts for electrical testing of equipment that is equipped with CONNEX bushings.



Picture may vary.

Technical Data

Article no.	827 186 210	
Size	0	
Max. system voltage	U _m (kV)	24
Rated lightning impulse withstand voltage (BIL)	(kV)	125
Rated power frequency withstand voltage	1 min (kV)	54
Nominal current	I _N (A)	250
DC voltage test	15 min 6 x U ₀ (kV)	72
Thread	G	M12